



Oxford Cambridge and RSA

Friday 19 November 2021 – Afternoon

GCSE (9–1) Computer Science

J276/02 Computational thinking, algorithms and programming

Time allowed: 1 hour 30 minutes



Do not use:

- a calculator



Please write clearly in black ink. **Do not write in the barcodes.**

Centre number

--	--	--	--	--

Candidate number

--	--	--	--

First name(s)

Last name

INSTRUCTIONS

- Use black ink.
- Write your answer to each question in the space provided. If you need extra space use the lined pages at the end of this booklet. The question numbers must be clearly shown.
- Answer **all** the questions.

INFORMATION

- The total mark for this paper is **80**.
- The marks for each question are shown in brackets [].
- This document has **16** pages.

ADVICE

- Read each question carefully before you start your answer.

Answer **all** the questions.

1 ASCII, extended ASCII and Unicode are all examples of character sets.

(a) Tick (✓) **one or more** boxes in each row to identify whether each statement applies to each character set.

	ASCII	Extended ASCII	Unicode
Can represent thousands of different characters, including Russian and Chinese symbols.			
Can represent European characters such as ç or â.			
Uses different character codes for upper-case and lower-case letters.			

[3]

(b) The character **D** is represented by the binary ASCII code **1000100**

Give the ASCII code for the following characters in binary.

E

.....

H

.....

[2]

(c) Sound data is also sampled and stored in binary.

A 30-second section of sound data is sampled at a rate of 48 KHz using 24 bits per sample.

(i) Describe the data that is recorded when sound is sampled.

.....
.....
.....
..... [2]

(ii) Explain what is meant by a sample rate of **48 KHz**.


.....
.....
.....
..... [2]

(iii) Describe how the file size of the sound recording could be reduced.

.....
.....
.....
.....
.....
.....
.....
.....
..... [4]

(c) For the next part of the experiment, Taylor needs to be able to enter 10 values and count how many of the values are over 50, outputting this value once all values have been entered.

(i) Complete the following flowchart to implement this algorithm.



[5]

4 A programmer declares the following variables.

```
first = "Computer Science"  
second = "is great"
```

(a) State **one** difference between a variable and a constant.

.....
..... [1]

(b) State the output from the following lines of program code.

(i) `print(first.length)`

..... [1]

(ii) `print(second.length DIV 3)`

..... [1]

(iii) `print(3 ^ 2)`

..... [1]

(c) Strings can be concatenated (joined together) using the + operator. For example, `print("Maths " + second)` will output `Maths is great`

Use string manipulation with the variables `first` and/or `second` to produce the following output.

(i) `great`

.....
..... [1]

(ii) `Computer`

.....
..... [1]

(iii) `Science is great`

.....
..... [1]

5 (a) Convert the denary value **178** into an 8-bit binary number.

.....
.....
.....
..... [2]

(b) Computers make use of electronic switches called transistors.

Describe how transistors can be used to store a value in binary.

.....
.....
.....
..... [2]

(c) Convert the binary value **11000111** into hexadecimal.

.....
.....
.....
..... [2]

(d) Azmi says, "hexadecimal is used because it takes up less storage space in the computer's memory than binary."

Tick **one** box to identify whether Azmi is correct. Justify your answer.

	Tick (✓)
Correct	
Incorrect	

Justification

.....
.....
..... [2]

- (e) Binary shifts can be used for multiplication and division.

Draw **one** line from each shift on the left to its correct outcome on the right.

Binary shift	Outcome
Right shift of 2 places on 1010 1000	0011 1010, divides by 4 with a loss of precision
Left shift of 1 place on 0010 1101	0010 1010, divides by 4
Right shift of 2 places on 1110 1001	0101 1010, multiplies by 2
Left shift of 3 places on 0001 1111	1111 1000, multiplies by 8

[3]

- (f) Add the following 8 bit binary integers, giving your answer in binary.

$$\begin{array}{r}
 00110110 \\
 + 10010110 \\
 \hline
 \end{array}$$

[2]

11
BLANK PAGE

PLEASE DO NOT WRITE ON THIS PAGE

- 6 OCRBlocks is a game played on a 5×5 grid. Players take it in turns to place blocks on the board. The board is stored as a two-dimensional (2D) array with the identifier `gamegrid`

Fig. 6.1 shows that players A and B have placed three blocks each so far.

	0	1	2	3	4
0	A			B	
1					
2		B			
3	A		B		
4			A		

Fig. 6.1

The function `checkblock()` checks whether a square on the board has been filled. When `checkblock(4, 2)` is called, the value "A" is returned.

```
function checkblock(r,c)
    if gamegrid[r,c] == "A" or gamegrid[r,c] == "B" then
        outcome = gamegrid[r,c]
    else
        outcome = "FREE"
    endif
    return outcome
endfunction
```

(a) Give the returned value when the following statements are called.

Function call	Returned value
<code>checkblock(2, 1)</code>	
<code>checkblock(3, 0)</code>	
<code>checkblock(2, 3)</code>	

[3]

(b) State **one** feature of `checkblock()` that shows that it is a function and not a procedure.

.....
..... [1]

(c) When `checkblock(-1, 6)` is called, an error is produced.

(i) State why this function call will produce an error.

.....
..... [1]

(ii) Describe how validation could be added in to the `checkblock()` function to stop this error from occurring.

.....
.....
.....
.....
.....
.....
..... [3]

ADDITIONAL ANSWER SPACE

If additional space is required, you should use the following lined page(s). The question number(s) must be clearly shown in the margin(s).

A large area of lined paper for writing. It features a vertical margin line on the left side and horizontal dotted lines for writing. The lines are evenly spaced and extend across the width of the page.

A large rectangular area for writing, bounded by a solid vertical line on the left and horizontal dotted lines on the top, bottom, and right.



Copyright Information

OCR is committed to seeking permission to reproduce all third-party content that it uses in its assessment materials. OCR has attempted to identify and contact all copyright holders whose work is used in this paper. To avoid the issue of disclosure of answer-related information to candidates, all copyright acknowledgements are reproduced in the OCR Copyright Acknowledgements Booklet. This is produced for each series of examinations and is freely available to download from our public website (www.ocr.org.uk) after the live examination series. If OCR has unwittingly failed to correctly acknowledge or clear any third-party content in this assessment material, OCR will be happy to correct its mistake at the earliest possible opportunity.

For queries or further information please contact The OCR Copyright Team, The Triangle Building, Shaftesbury Road, Cambridge CB2 8EA.

OCR is part of the Cambridge Assessment Group; Cambridge Assessment is the brand name of University of Cambridge Local Examinations Syndicate (UCLES), which is itself a department of the University of Cambridge.